

AlphaRefuge™ 2100 Series (1-10 System)		
RCC2500 Series Refuge Command Center	89mA on hook 107mA off hook	2.136w 2.568w
RCB2100 Series Refuge Call Boxes Battery Output: 1400mAh	370mA	8.88w
PWR2410A Power Supply	70mA	8.4w

AlphaRefuge™ 2400 Series (1-112 System)		
RCC2500 Series Refuge Command Center Note: the first active phone adds 7.21w, each additional phone adds 4.6w	170mA	20.4w
PWRAPC Power Supply Output: 600w @ 1000VA Battery: 24v, 12 Amp	166mA	19.92w
PWRAPC112 Power Supply Output: 1920w @ 1920VA Battery: 24v, 15 Amp	870mA	104.4w
Supervisor (12v) Up to 36 Zone: Lights Off, Relay Inactive Lights On, Relay Inactive Lights On, Relay Active	150mA 190mA 230mA	1.8w 2.28w 2.76w
56-79 Zone: 92 Zone:	458mA 691mA	5.5w 8.3w
AR-UPSMON	28mA	.67w



NOTE: due to continuous product improvement, all specifications, data, information may be subject to change without notice.

 <p>42 Central Drive, Farmingdale NY 11735-1202 (631) 777-5500 Fax: (631) 777-5599 TOLL-FREE Technical Line 1-800-666-4800 Email: info@alphacomunications.com</p>	<p>AlphaRefuge™ System 2100 Series and 2400 2400 Series Power Consumption Chart.</p>
--	---