


1. INSTALL THE FLUSH (RED) PLASTIC BACK BOX INTO THE WALL, ADJACENT TO THE DESK (OR TABLE TOP) WHERE THE DESK ADAPTOR SHALL BE PLUGGED-IN.
2. CONNECT YOUR WIRES ONTO THE PAINTED WHITE FACEPLATE, TO TERMINALS 1-24 (AS REQUIRED) AS SHOWN BELOW.
3. FASTEN THE WHITE FACEPLATE ONTO THE FLUSH BACK BOX WITH THE FOUR (4) FLAT HEAD SCREWS PROVIDED.
4. REMOVE THE MONITOR AND HANDSET FROM THE SURFACE PLASTIC HOUSING AND SCREW THE HOUSING ONTO THE DESK ADAPTOR, MAKING SURE THAT THE PIG-TAIL WIRES SUPPLIED HAVE BEEN PUSHED (FED) INTO THE MONITOR HOUSING.
5. CONNECT WIRES AS SHOWN BELOW, RE-ATTACH MONITOR AND HANDSET, AND PLUG THE DESK ADAPTOR (MALE PLUG) INTO THE WHITE FACEPLATE IN THE WALL.

TERMINAL# AND CORRESPONDING WIRE COLOR =====	PC BOARD IN HOUSING BEHIND HANDSET =====	HT2003/2 TYPE HANDSET =====	HT2006/5 TYPE HANDSET =====	HT2006/10 TYPE HANDSET =====
1 WHITE-----	COAX (CENTER)		See handset connections	
2 BLACK or YELLOW--	COAX (SHIELD)		below for the type of	
			handset you are using!!	
3 ORANGE-----	CT		Note:	
4 BLACK-----	-16V (-)		Please observe polarity on	
5 BLUE-----	-16V (+)		the 16V connections!!	
			NOTE: ABOVE WIRES ARE FROM SMALL GREY JACKETED CABLE	

NOTE: BELOW WIRES ARE FROM LARGER WHITE JACKETED CABLE

6 BROWN or ORANGE-----		M-----	M-----	M-----
7 PINK-----		O-----	O-----	O-----
8 YELLOW-----		T-----	T-----	T-----
9 GREEN-----		S-----	R-----	R-----
10 RED or BLUE-----		1-----	S-----	S-----
11 PURPLE-----		2-----	Z-----	Z-----
12 GREY-----			E-----	E-----
13 WHITE-----			1-----	1-----
14 STRIPE+BLACK-----			2-----	2-----
15 STRIPE+BROWN-----			3-----	3-----
16 STRIPE+RED-----			4-----	4-----
17 STRIPE+ORANGE-----			5-----	5-----
18 STRIPE+PINK-----				6-----
19 STRIPE+YELLOW-----				7-----
20 STRIPE+GREEN-----				8-----
21 STRIPE+BLUE-----				9-----
22 STRIPE+GREY-----				10-----
23 Unused				
24 Unused				

	<p>Typical Wiring Diagram for the S.T.R.™ TZ25 Series Desk/Tabletop Adaptor for VMH25 and VMH25A Series Video-Intercom Monitor(s).</p>
<p>42 Central Drive, Farmingdale NY 11735-1202 (631) 777-5500 Fax: (631) 777-5599 TOLL-FREE Technical Line 1-800-666-4800 Email: info@alpha-comm.com</p>	