

NOTES:

- PLEASE CONSULT ALPHA COMMUNICATIONS FOR SPECIFIC RESTRICTIONS ON REPLACING TA205'S (OR TA205A'S OR TA205B'S WITH TA206'S AND VICE-VERSA.

CORRESPONDING

TA205	TERMINAL CONNECTIONS		TA206	TERMINAL CONNECTIONS
A	<----->	1		
B	<----->	2		
C	<----->	6		
D	<----->	3		
X	<----->	4		

NOTES: POLARITY MUST BE OBSERVED ON ALL TERMINALS SHOWN.

TA205 HANDSETS MUST HAVE TWISTED PAIRS FOR COMMON TERMINALS 'A' & 'B' AND 'C' & 'D'. (SAME FOR TA205A /B HANDSETS).

TA206 HANDSETS MUST HAVE TWISTED PAIRS FOR COMMON TERMINALS '1' & '2' AND '6' & '3'.

TA205 DOOR RELEASE TERMINALS ARE 'A' AND 'D'
TA205 MICROPHONE TERMINALS ARE 'A' AND 'B'
TA205 RECEIVER TERMINALS ARE 'C' AND 'D'
TA205 SELECTIVE (CALL/RING) TERMINAL IS 'X'
(SAME FOR TA205A HANDSETS)

TA206 DOOR RELEASE TERMINALS ARE '1' AND '3'
TA206 MICROPHONE TERMINALS ARE '1' AND '2'
TA206 RECEIVER TERMINALS ARE '6' AND '3'
TA206 SELECTIVE (CALL/RING) TERMINAL IS '4'

ALPHA COMMUNICATIONS ! SPECIAL CROSS-REFERENCE WIRING ! Diagram# !
42 CENTRAL DRIVE ! GUIDE TO REPLACE TEKTONE'S TA205A ! WD2056 !
FARMINGDALE NY 11735 ! (OR TA205B) AND TA206 HANDSETS !=====!
631-777-5500 ! WITH EACH OTHER. ! 09/19/00 !